


## SUPER HIGH POWER INTELLIGENT PHASE COMBINED SYSTEM IPC<sup>™</sup> SERIES 400W / 500W / 600W KU-BAND GAN SSPA/ BUC



Smaller, Lighter and more Powerful IPC<sup>™</sup> Series Intelligent Phase Combined System allows significant high combing efficiency utilizing IRT Technologies World's Smallest and Lightest SSPAs / BUCs. The Phase Combined System provides high reliability, soft failure mode and shorter MTTR this is why IRT offers 3 years warranty for this system!

The IRT Technologies IPC<sup>™</sup> series 400W / 500W / 600W Ku-Band GaN powered SSPA / BUC are very compact, light and extremely powerful. Super compact system at only 26"x38.5"x12", this Ku-Band 400W / 500W / 600W IPC<sup>™</sup> product family is the most powerful and feature rich for its size: up to 600W at saturated power. IRT IPC<sup>®</sup> features best in class RF characteristics, RF sample port, true RMS power measurements, extensive monitor and control capabilities enabled via Ethernet, Serial and/or Analog Interfaces. IPC<sup>™</sup> remarkably compact size and high thermal efficiency results in overall system size and cost reduction making it the ideal candidate for mobile and fixed VSAT applications.

## **KEY FEATURES**

- Supercompact up to 600W PSAT in 26"x38.5"x12" only!
- Available in both SSPA and BUC versions
- Superior RF performance:
  - ✓ High Linearity
  - ✓ PSAT up to 58 dBm
  - ✓ Wide dynamic range of Gain Control
- High Combining Efficiency over full frequency band
- RF Overdrive Protection
- Available in both Standard and Extended Ku-Band

- Field Replaceable Power Supply
- Input and Output True RMS Power Detection
- Configuration via RS-232 Serial Console, Packet Protocol RS-485 - User friendly HTTP based GUI and SNMP Support
- Automated Level Control (ALC) Option
- Internal 10MHz Reference Option (BUC version)
- Status LED
- Phase Mismatch Alarm
- Power distribution box for ease of installation

800 Boulevard Saint-Jose La Prairie, QC Canada J5R 6W9 +1-450-444-1227 www.irttechnologies.com Canada (Headquarters) sales@irttechnologies.com

USA usa\_sales@irttechnologies.com

**CONNECTING THE WORLD TOGETHER** 

Europe europe\_sales@irttechnologies.com

Asia Pacific asia\_sales@irttechnologies.com





## IPC<sup>™</sup> Series 400W / 500W / 600W Ku-Band Phase Combined SSPA/BUC System Specification

| Parameter   | 400W                    | 500W   | 600W                     |  |
|---|-------------------------|--|--------------------------|--|
| RF Performance  |                         |  |                          |  |
| RF Frequency Range-Available                          |                         | 14-14.5GHz 13.75-14.5GHz   |                          |  |
| Saturated Power (frequency info entered)              | 56dBm typ               | 57dBm typ  | 58dBm typ                |  |
| Linear Power  | 53dBm min               | 54dBm min  | 55dBm min                |  |
| Gain  | SSPA- 68dB m            | SSPA- 68dB min, 70dB typ; BUC-75dB min, 77dB typ   |                          |  |
| Gain Flatness   |                         | +/-1.5dB max over full band;<br>+/-0.5dB max over any 40MHz                                    |                          |  |
| Gain Stability over temperature                       | +/                      | +/-1.5dB over full temperature range   |                          |  |
| Gain Stability over input power                       | 3dB typ 4               | 3dB typ 4dB max from 10dB back off to rated power  |                          |  |
| Gain Control  |                         | 20dB min dynamic range   |                          |  |
| Linearity: 2 tone IMD Spectral Re-growth              | -30dBc                  | -24dBc at P linear<br>-30dBc for QPSK at 1.5xsymbol rate at Plinear                            |                          |  |
| Output Spurious: Non-signal related<br>Signal related |                         | SSPA -65dBc max; BUC -60dBc max<br>SSPA -60dBc max; BUC -55dBc max                             |                          |  |
| BUC Version Only:                                     |                         |  |                          |  |
| External Reference Frequency                          |                         | 10MHz multiplexed with IF In   |                          |  |
| External Reference Required Phase Noise               | -130dBc/Hz @100Hz; -140 | dBc/Hz@1kHz; -150dBc/Hz@   | 10kHz; -155dBc/Hz@100 kH |  |
| Up-Converter Phase Noise                              |                         | -68dBc/Hz @ 100Hz; -80dBc/Hz @ 1kHz; -90dBc/Hz @ 10kHz<br>-95dBc/Hz @ 100kHz -115dBc/Hz @ 1MHz |                          |  |
| Power   |                         |  |                          |  |
| AC Voltage Range                                      | 190                     | 190-265VAC 50-60Hz auto-ranging PFC  |                          |  |
| Power Consumption at rated power                      | 3000W                   | 3000W 3500W 4000W  |                          |  |
| Power Consumption at 3 dB back off                    | 2500W                   | 2900W  | 3500W                    |  |
| Mechanical  |                         |  |                          |  |
| Size  |                         | 26"38.5"x12"   |                          |  |
| Weight  |                         | 125lbs   |                          |  |
| Cooling   |                         | Forced Air   |                          |  |
| Operating temperature                                 |                         | -40°C to +55°C   |                          |  |
| Relative Humidity                                     |                         | Up to 100% condensing  |                          |  |
| Interfaces  |                         |  |                          |  |
| RF/IF Input Connector                                 |                         | N-type female  |                          |  |
| RF Output Connector                                   |                         | WR75 grooved   |                          |  |
| RF Sample   |                         | N-type female  |                          |  |
| AC Power In   |                         | MS3112E12-3P   |                          |  |
| M&C Interface-Serial, Analog and Ethernet             |                         | MS3112E14-19S  |                          |  |
| Redundant Interface                                   |                         | MS3112E14-19P  |                          |  |
| Part Numbering Information                            |                         |  |                          |  |
| IRT Part Number                                       | 400W                    | 500W   | 600W                     |  |
| SSPA Version  | ТРА-КХВ0560-НРС0        | ТРА-КХВ0570-НРСО   | ТРА-КХВ0580-НРСО         |  |
| BUC Version   | ТРВ-КХВ0560-НРС0        | ТРВ-КХВ0570-НРСО   | TPB-KXB0580-HPC0         |  |

\*Contact us for detailed ordering information at <a href="mailto:sales@irttechnologies.com">sales@irttechnologies.com</a>

\*\*Specifications are subject to change without prior notice

Rev.02



800 Boulevard Saint-Jose La Prairie, QC Canada J5R 6W9 +1-450-444-1227 www.irttechnologies.com Canada (Headquarters) sales@irttechnologies.com

USA usa\_sales@irttechnologies.com europe\_sales@irttechnologies.com Asia Pacific

n asia\_sales@irttechnologies.com

Europe